



CLEVERTRONICS L10 HAWKEYE MAINTAINED LED TUBE EMERGENCY BATTEN WITH L10 BATTERY, LED POD AND MICROWAVE SENSOR CONTROL



PRODUCT INFORMATION

Catalogue Number	LBS2L2S-DIF-MS-CT
Description	Wide Body Batten with LED Tubes, D63 LED Emergency Pod & L10 Lithium battery
Construction	Powder Coated Steel
Mounting	Surface Mount
Dimensions L x W x H	666mm x 120mm x 110mm
Operating Mode	Sustained/Combined Non-Maintained. On/off control of the LED tube via switched active input. Non-Maintained LED emergency function.
Testing System	Clevertest
Diffuser	Prismatic
LED Tube(s)	2 x 600mm LED Tube 840 G13 880lm 50,000 Hours
Operating Voltage	240V, 50Hz
Charging Method	Intelligent current limited constant voltage charger
Emergency Lamp Source	2 x 3W LED (Lifetime warranty on the lamp head and loom assembly) No dome cover required
IP Rating	IP20
Operating Temperature	10° to 40°C
Power Consumption	16.6W (Lamp ON) 1W (Lamp OFF)
AS2293 Classification	C ₀ = D63 C ₉₀ = D63

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
3170025	Lamp, LED Tube 8W 4000K
1100640	Lamp, Lifelight Pro Head and Heatsink
1120320	Lamp Holder T8
2300060	Diffuser 14/18W Wide
2900012	Shanghai End Cap
1530050	Battery, L10 3.3V 2.5Ahr
8002390	PCA, Lifelight Pro L10 Driver #CT10142-L5
8001730	Network: Clever-Test Node
1190116	Motion Sensor Assembly