



CLEVERTRONICS 240V LED TUBE BARE BATTEN WITH MICROWAVE SENSOR



PRODUCT INFORMATION

Catalogue Number	FBS1L2-DIF-MS
Description	Wide body bare batten with LED tube and Microwave sensor control of the fluorescent lamps (on/off).
Construction	Powder coated steel and ABS/Polycarbonate end caps
Diffuser	Acrylic Prismatic
Mounting	Surface mount
Dimensions L x W x H	613mm x 112mm x 95mm
Lamp(s)	1x 600mm LED T8 tube, Col. 840, 880lm per tube, 50,000hours
Operating Voltage	250V AC; 50Hz
Power Consumption	8.6 Watts (lamps on) 0.6 Watts (lamps off)
IP Rating	IP20
Operating Temperature	1°C to 40°C

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
3170025	LED TUBE 8W 4000K, 0.6m, 60°C
1120320	LAMPHOLDER, t/s T8 Sabre Battens, 2 Part
1190116	SENSOR: Microwave Motion, IP20, HC009S

240V