




CLEVERTRONICS 1 x 36W WIRE GUARD BATTEN WITH MICROWAVE MOTION SENSOR CONTROL



PRODUCT INFORMATION

Catalogue Number	FBS136-WG-A2-MS
Description	1 x 36 Watt Wire Guard Batten with Microwave Sensor Control On/Off function only with factory pre-set on time after last presence detection.
Construction	Powder Coated Steel body
Mounting	Surface Mount
Dimensions L x W x H	1226mm x 115mm x 108mm
Operating Mode	240 Volt
Ballast	High Frequency Electronic Ballast EEI = A2 and pre-heating function
Sensor	360° Microwave Motion Detector
Lamp(s)	T8 36W/840 Cool White Tri-Phosphorous
Operating Voltage	240V
Power Consumption	36 Watts (5.7W Standby)
IP Rating	IP20
Operating Temperature	10° to 40°C

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1310212	Ballast, Philips HF-P 1x36W EEI =A2
3100380	Lamp(s) T8 36W/840 COOLWHITE TUBE
1120320	Lamp Holder T8
2300110	Prismatic Diffuser
2900012	Shanghai End Caps
1190110	Motion Sensor Assembly