

CLEVERTRONICS LP LED TUBE DIFFUSED BATTEN & MICROWAVE SENSOR (Zoneworks)



PRODUCT INFORMATION

Catalogue Number	CBS1L2S-LT-DIF-MS-ZW
Description	LP Premium 1x LED tube Diffused Batten with LED Emergency POD and Microwave Sensor Control of the Lamps (on/off)
Construction	Powder coated Steel body, Acrylic Prismatic Diffuser and ABS/Polycarbonate End Caps
Dimensions L x W x H	666mm x 120mm x 110mm
Operating Mode	Sustained
Testing System	Zoneworks computerised testing
Battery	Lithium Iron Phosphate, 3.2V 3200mAh
Charging Method	Intelligent Current Limited Constant Voltage
Diffuser	Prismatic
Lamp(s)	1x Philips CorePro LEDtube T8, Col. 840, 30,000hours
Operating Voltage	240V AC; 50Hz
Total lumen output	720 lm @ 72lm/W
Power Consumption	10 Watts (Lamps ON), 1.5 Watts (Lamps OFF)
IP Rating	IP20
Operating Temperature	1°C to 40°C
AS2293 Classification	C ₀ =D40 C ₉₀ =D40

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1550050	Battery, LP 3.2V 3200mAh 70mm lead, no Bracket
3170030	LED TUBE 8W/840, 0.6m
CLIFE-CKIT-NP	Lifelight, Control Only, LP, No Plug
1190116	SENSOR: Microwave Motion, IP20, HC009S
8001450	PCA: Powerline Node ZW, #CT10310-A6

ZONEWORKS

LP LITHIUM IRON
PHOSPHATE

PREMIUM

PROVEN PROJECT PERFORMANCE

Version: March 2018-I

www.clevertronics.com.au