

CLEVERTRONICS LP 600MM (2FT) NON-MAINTAINED BATTEN REPLACEMENT (Zoneworks)



| PRODUCT INFORMATION | |
|-----------------------|---|
| Catalogue Number | CBS2N-ZW |
| Description | LP Premium 600mm (2ft) Non-Maintained Bare Batten Replacement Utilising the Lifelight - High Performance, Emergency Light with Premium Lithium Battery Technology |
| Construction | Powder coated Steel body and ABS/Polycarbonate End Caps |
| Mounting | Surface mount |
| Dimensions L x W x H | 610mm x 110mm x 50mm |
| Operating Mode | Non-maintained |
| Testing System | Zoneworks computerised testing |
| Charging Method | Intelligent Current Limited Constant Voltage |
| Lamp(s) | LED (Lifetime warranty on the lamp head and loom assembly) No dome cover required |
| Operating Voltage | 240V AC; 50Hz |
| Power Consumption | 1.0W Standby (3.9W during first 16hr charge) |
| IP Rating | IP20 |
| Operating Temperature | 1°C to 40°C |
| AS2293 Classification | C ₀ =D40 C ₉₀ =D40 |

| REPLACEMENT PARTS | |
|-------------------|---------------------------------------|
| PART NUMBER | DESCRIPTION |
| 1550010 | BATT:LP 3.2V 3200mAh 200mm lead,BRKT. |
| 1100930 | CLIFE Head Assembly, Round, 1LED |
| CLIFE-CKIT-NP | Lifelight, Control Only, LP, No Plug |
| 8001450 | PCA:Powerline Node ZW, #CT10310-A6 |



Version: November 2016-I www.clevertronics.com.au

